

Atty Docket No. RAYTP0160US

PHASED ARRAY SOURCE OF ELECTROMAGNETIC RADIATION

by

James G. Small

CERTIFICATION UNDER 37 CFR 1.10

I hereby certify that the attached patent application (along with any other paper referred to as being attached or enclosed) is being deposited with the United States Postal Service on this date November 27, 2001, in an envelope as "Express Mail Post Office to Addressee" Mailing Label Number EF297165164US addressed to the: Box Patent Application, Assistant Commissioner for Patents, Washington, D.C. 20231.

Mark D. Saralino

(Typed or Printed Name of Person Mailing Paper)



(Signature of Person Mailing Paper)

TITLE: PHASED ARRAY SOURCE OF ELECTROMAGNETIC RADIATION


Technical Field

5 The present invention relates generally to electromagnetic radiation sources,
and more particularly to a phased array source of electromagnetic radiation.

Background of the Invention

10 Magnetrons are well known in the art. Magnetrons have long served as
highly efficient sources of microwave energy. For example, magnetrons are
commonly employed in microwave ovens to generate sufficient microwave energy for
heating and cooking various foods. The use of magnetrons is desirable in that they
operate with high efficiency, thus avoiding high costs associated with excess power
consumption, heat dissipation, etc.

15 Microwave magnetrons employ a constant magnetic field to produce a rotating
electron space charge. The space charge interacts with a plurality of microwave
resonant cavities to generate microwave radiation. Heretofore, magnetrons have
been generally limited to maximum operating frequencies below about 100 Gigahertz
(Ghz). Higher frequency operation previously has not been considered practical for
perhaps a variety of reasons. For example, extremely high magnetic fields would be
20 required in order to scale a magnetron to very small dimensions. In addition, there
would be considerable difficulty in fabricating very small microwave resonators.
Such problems previously have made higher frequency magnetrons improbable and
impractical.

25  > Recently, the applicant has developed a magnetron that is suitable for
operating at frequencies heretofore not possible with conventional magnetrons. This
high frequency magnetron is capable of producing high efficiency, high power
electromagnetic energy at frequencies within the infrared and visible light bands,
and which may extend beyond into higher frequency bands such as ultraviolet, x-ray,
etc. As a result, the magnetron may serve as a light source in a variety of
30 applications such as long distance optical communications, commercial and

industrial lighting, manufacturing, etc. Such magnetron is described in detail in commonly assigned, copending United States patent application Serial No. 09/584,887, filed on June 1, 2000, and Serial No. 09/798,623, filed on March 1, 2001, the entire disclosures of which are both incorporated herein by reference.

5 This high frequency magnetron is advantageous as it does not require extremely high magnetic fields. Rather, the magnetron preferably uses a magnetic field of more reasonable strength, and more preferably a magnetic field obtained from permanent magnets. The magnetic field strength determines the radius of rotation and angular velocity of the electron space charge within the interaction region between the cathode and the anode (also referred to herein as the anode-cathode space). The anode includes a plurality of small resonant cavities which are sized according to the desired operating wavelength. A mechanism is provided for constraining the plurality of resonant cavities to operate in what is known as a pi-mode. Specifically, each resonant cavity is constrained to oscillate pi-radians out of phase with the resonant cavities immediately adjacent thereto. An output coupler or coupler array is provided to couple optical radiation away from the resonant cavities in order to deliver useful output power.

10
15
20
25 Nevertheless, there remains a strong need in the art for even further advances in the development of high frequency electromagnetic radiation sources. For example, there remains a strong need for a device with fewer loss mechanisms and hence even further improved efficiency. More particularly, there is a strong need for a device which does not utilize a plurality of small resonant cavities. Such a device would offer greater design flexibility. Moreover, such a device would be particularly well suited for producing electromagnetic radiation at very short wavelengths.

Summary of the Invention

30 A phased array source of electromagnetic radiation (referred to herein as a "phaser") is provided in accordance with the present invention. The phaser converts direct current (dc) electricity into single -frequency electromagnetic radiation. Its

wavelength of operation may be in the microwave bands or infrared light or visible light bands, or even shorter wavelengths.

In the exemplary embodiments, the phaser includes an array of phasing lines and/or interdigital electrodes which are disposed around the outer circumference of an electron interaction space. During operation, oscillating electric fields appear in gaps between adjacent phasing lines/interdigital electrodes in the array. The electric fields are constrained to point in opposite directions in adjacent gaps, thus providing so-called "pi-mode" fields that are necessary for efficient magnetron operation.

An electron cloud rotates about an axis of symmetry within the interaction space. As the cloud rotates, the electron distribution becomes bunched on its outer surface forming spokes of electronic charge which resemble the teeth on a gear. The operating frequency of the phaser is determined by how rapidly the spokes pass from one gap to the next in one half of the oscillation period. The electron rotational velocity is determined primarily by the strength of a permanent magnetic field and the electric field which are applied to the interaction region. For very high frequency operation, the phasing lines/interdigital electrodes are spaced very closely to permit a large number of gap passings per second.

According to one particular aspect of the invention, an electromagnetic radiation source is provided. The source includes an anode and a cathode separated by an anode-cathode space. Electrical contacts are provided for applying a dc voltage between the anode and the cathode and establishing an electric field across the anode-cathode space. At least one magnet is arranged to provide a dc magnetic field within the anode-cathode space generally normal to the electric field. A plurality of openings are formed along a surface of the anode which defines the anode-cathode space, whereby electrons emitted from the cathode are influenced by the electric and magnetic fields to follow a path through the anode-cathode space and pass in close proximity to the openings. The source further includes a common resonator which receives electromagnetic radiation induced in the openings as a result of the electrons passing in close proximity to the openings, and which reflects

the electromagnetic radiation back towards the openings and produces oscillating electric fields across each of the openings at a desired operating frequency.

According to another aspect of the invention, an electromagnetic radiation source is provided which includes an anode and a cathode separated by an anode-cathode space. The source further includes electrical contacts for applying a dc voltage between the anode and the cathode and establishing an electric field across the anode-cathode space. In addition, the source includes at least one magnet arranged to provide a dc magnetic field within the anode-cathode space generally normal to the electric field, and an array comprising N pin-like electrodes forming at least a part of the anode and arranged in a pattern to define the anode-cathode space. Furthermore, the source includes at least one common resonant cavity in proximity to the electrodes. The electrodes are spaced apart with openings therebetween, and electrons emitted from the cathode are influenced by the electric and magnetic fields to follow a path through the anode-cathode space and pass in close proximity to the openings to establish a resonant electromagnetic field within the common resonant cavity.

To the accomplishment of the foregoing and related ends, the invention, then, comprises the features hereinafter fully described and particularly pointed out in the claims. The following description and the annexed drawings set forth in detail certain illustrative embodiments of the invention. These embodiments are indicative, however, of but a few of the various ways in which the principles of the invention may be employed. Other objects, advantages and novel features of the invention will become apparent from the following detailed description of the invention when considered in conjunction with the drawings.

Brief Description of the Drawings

Fig. 1 is an environmental view of a phased array source of electromagnetic radiation (phaser) in accordance with the present invention as part of an optical communication system;

Fig. 2 is a cross-sectional view of a phaser including phasing lines in accordance with one embodiment of the present invention;

Fig. 3 is a cross-sectional top view of the phaser of Fig. 2 in accordance with the present invention, taken along line 3--3;

5 Figs. 4a and 4b are perspective views of even-numbered wedges and odd-numbered wedges, respectively, which are suitable for forming an anode structure for the phaser of Fig. 2 in accordance with the present invention;

Fig. 5 is a cross-sectional view of a phaser with interdigital electrodes and a wide anode construction in accordance with another embodiment of the present invention;

Fig. 6 is a cross-sectional top view of the interaction region of the phaser of Fig. 5 in accordance with the present invention, taken along line 6--6;

Fig. 7 is a schematic view of the interaction region of the phaser of Fig. 5 in accordance with the present invention;

15 Fig. 8 is a cross-sectional view of a phaser with interdigital electrodes and a narrow anode construction in accordance with still another embodiment of the present invention;

Fig. 9 is a cross-sectional top view of the interaction region of the phaser of Fig. 8 in accordance with the present invention, taken along line 9--9;

20 Fig. 10 is a schematic front view of the interaction region of the phaser of Fig. 8 in accordance with the present invention;

Fig. 11 is a schematic front view of an alternative embodiment of the anode configuration in accordance with the present invention; and

25 Fig. 12 is a cross-sectional view of a phaser with floating interdigital electrodes in accordance with another embodiment of the present invention.

Detailed Description of the Invention

Referring initially to Fig. 1, a high frequency communication system 20 is shown. In accordance with the present invention, the communication system 20 includes a phased array source of electromagnetic radiation (phaser) 22. The

phaser 22 serves as a high-efficiency source of high frequency electromagnetic radiation. Such radiation may be, for example, in the microwave bands or infrared light or visible light bands, or even shorter wavelengths. The output of the phaser 22 may be light used to communicate information optically from point-to-point. Although
5 the phaser 22 is described herein in the context of its use in an optical band communication system 20, it will be appreciated that the phaser 22 has utility in a variety of other applications. The present invention contemplates any and all such applications.

Sub 22 *7* As is shown in Fig. 1, the phaser 22 serves to output optical radiation 24 such as coherent light in the infrared, ultraviolet or visible light region, for example. The optical radiation is preferably radiation which has a wavelength corresponding to a frequency of 100 Ghz or more. In a more particular embodiment, the phaser 22 outputs optical radiation having a wavelength in the range of about 10 microns to about 0.5 micron. According to an even more particular embodiment, the phaser 22
15 outputs optical radiation having a wavelength in the range of about 3.5 microns to about 1.5 microns. However, it will be appreciated that the phaser 22 has application even at frequencies substantially less 100 Ghz.

The optical radiation 24 produced by the phaser 22 passes through a modulator 26 which serves to modulate the radiation 24 using known techniques.
20 For example, the modulator 26 may be an optical shutter which is computer controlled based on data to be communicated. The radiation 24 is selectively transmitted by the modulator 26 as modulated radiation 28. A receiving device 30 receives and subsequently demodulates the modulated radiation 28 in order to obtain the transmitted data.

25 The communication system 20 further includes a power supply 32 for providing an operating dc voltage to the phaser 22. As will be explained in more detail below, the phaser 22 operates on a dc voltage provided between the cathode and anode. In an exemplary embodiment, the operating voltage is on the order of 1 kilovolt (kV) to 4 kV. However, it will be appreciated that other operating voltages
30 are also possible.

Fig 2 Referring now to Figs. 2 and 3, a first embodiment of the phaser 22 is shown. The phaser 22 includes a cylindrically shaped cathode 40 having a radius r_c . Included at the respective ends of the cathode 40 are endcaps 41. The cathode 40 is enclosed within a hollow-cylindrical shaped anode 42 which is aligned coaxially with the cathode 40 relative to axis A. The anode 42 has an inner radius r_a which is greater than r_c so as to define an electron interaction region or anode-cathode space 44 between an outer surface 48 of the cathode 40 and an inner surface 50 of the anode 42.

Fig 3 Terminals 52 and 54 respectively pass through an insulator 55 and are electrically connected to the cathode 40 to supply power to heat the cathode 40 and also to supply a negative (-) high voltage to the cathode 40. The anode 42 is electrically connected to the positive (+) or ground terminal of the high voltage supply via terminal 56. During operation, the power supply 32 (Fig. 1) applies heater current to and from the cathode 40 via terminals 52 and 54. Simultaneously, the power supply 32 applies a dc voltage to the cathode 40 and anode 42 via terminals 54 and 56. The dc voltage produces a dc electric field E which extends radially between the cathode 40 and anode 42 throughout the anode-cathode space 44.

Fig 4 The phaser 22 further includes a pair of magnets 58 and 60 located at the respective ends of the anode 42. The magnets 58 and 60 are configured to provide a dc magnetic field B in an axial direction which is normal to the electric field E throughout the anode-cathode space 44. As is shown in Fig. 3, the magnetic field B is into the page within the anode-cathode space 44. The magnets 58 and 60 in the exemplary embodiment are permanent magnets which produce a magnetic field B on the order of 2 kilogauss, for example. Other means for producing a magnetic field may be used instead (e.g., an electromagnet) as will be appreciated. However, one or more permanent magnets 58 and 60 are preferred particularly in the case where it is desirable that the phaser 22 provide some degree of portability, for example.

The crossed magnetic field B and electric field E influence electrons emitted from the cathode 40 to move in curved paths through the anode-cathode space 44.

With a sufficient dc magnetic field B, the electrons will not arrive at the anode 42, but return instead to the cathode 40.

Fig 2 *46* → The anode 42 has formed therein an even-numbered array of straight single-mode waveguides 59a and 59b (represented in phantom in Fig. 3). The waveguides 59a and 59b function as respective phasing lines and have dimensions which are selected using conventional techniques such that the waveguides operate in single-mode at the desired operating wavelength λ . The waveguides 59a and 59b extend radially (relative to the axis A) from the anode-cathode space 44, thru the body of the anode 42, to a common resonant cavity 66. In particular, each of the waveguides 59a and 59b include an opening at the inner surface 50 of the anode 42 into the anode-cathode space 44. At the outer surface 68 of the anode 42, the waveguides 59a and 59b open into the common resonant cavity 66. The openings of the waveguides 59a and 59b are evenly and alternately spaced circumferentially along the inner and outer surfaces of the anode 42. The gap between openings along the inner surface 50 is represented by G_p .

Fig 3 *47* → As is represented in Figs. 2 and 3, the waveguides 59a (nominally referred to herein as even-numbered waveguides) are relatively narrow waveguides compared to the waveguides 59b (nominally referred to herein as odd-numbered waveguides). The widths of the waveguides are selected such that the odd numbered waveguides 59b have a width W_b which is greater than the width W_a of the even numbered waveguides 59a so as to provide an additional $\frac{1}{2}\lambda$ phase delay compared to the even-numbered waveguides 59a at the operating wavelength λ . In the exemplary embodiment, four even-numbered waveguides 59a are arranged side-by-side in the axial direction along axis A, and three of the wider odd-numbered waveguides 59b are similarly arranged. It will be appreciated, however, that the particular number of waveguides arranged in the axial direction is a matter of choice and may be different depending on desired output power, etc.

The common resonant cavity 66 is formed around the outer circumference of the anode 42, and is defined by the outer surface 68 of the anode 42 and a cavity defining wall 70 formed within a resonant cavity structure 72. The wall 70 is curved

and forms a toroidal shaped resonant cavity 66. The radius of curvature of the wall 70 is on the order of 2.0 cm to 2.0 m, depending on the operating frequency.

As is shown in Figs. 2 and 3, the resonant cavity structure 72 forms a cylindrical sleeve which fits around the anode 42. The resonant cavity 66 is positioned so as to be aligned with the outer openings of the respective waveguides 59a and 59b. The resonant cavity 66 serves to constrain the oscillations thru the respective waveguides 59a and 59b so as to operate in the pi-mode as is discussed more fully below.

In addition, the cavity structure 72 may serve to provide structural support and/or function as a main housing of the device 22. The cavity structure 72 also facilitates cooling the anode 42 in the event of high temperature operation.

The common resonant cavity 66 includes at least one or more output ports 74 which serve to couple energy from the resonant cavity 66 out through a transparent output window 76 as output optical radiation 24. The output port(s) 74 are formed by holes or slots provided through the wall of the resonant cavity structure 72.

The structure shown in Figs. 2 and 3, together with the other embodiments described herein, is preferably constructed such that the anode-cathode space 44 and resonant cavity 66 are maintained within a vacuum. This prevents dust or debris from entering into the device and otherwise disturbing the operation thereof.

The resonant cavity 66 is designed using conventional techniques to have an allowed mode at the desired operating frequency (i.e., at the desired operating wavelength λ). Such techniques are known, for example, in connection with optical resonators conventionally used with laser devices. In the exemplary embodiment, the waveguides 59a and 59b are tapered waveguides. The waveguides 59a and 59b are designed to cut off frequencies which correspond to all possible resonant modes of the resonant cavity 66 below the desired operating frequency. In addition, the waveguides 59a and 59b are dimensioned to provide the aforementioned relative $\frac{1}{2}$ wavelength phase difference at the operating frequency and only at that frequency.

The spacing G_p between openings of adjacent waveguides at the inner anode surface 50 is selected to optimize gain at the desired operating wavelength λ and to suppress oscillations at higher frequencies. The result is that a rotating electron cloud that is formed within the anode-cathode space 44 interacts with pi-mode electric fields at the inner anode surface 50, and pi-mode oscillation occurs.

More particularly, during operation power is supplied to the cathode 40 and anode 42. Electrons are emitted from the cathode 40 and follow the aforementioned curved paths through the anode-cathode space 44 and pass in close proximity to the openings of the waveguides 59a and 59b. As a result, an electromagnetic field is induced within the waveguides 59a and 59b. Electromagnetic radiation in turn travels through the waveguides 59a and 59b and enters the common resonant cavity 66. Electromagnetic radiation within the cavity 66 begins to resonate and is in turn coupled back through the waveguides 59a and 59b toward the anode-cathode space 44.

As a result, the electrons emitted from the cathode 40 tend to form a rotating electron cloud within the anode-cathode space 44. Oscillating electric fields appear in the gaps between the openings of the waveguides 59a and 59b at the inner surface 50 of the anode 42. Because the waveguides 59a and 59b are $\frac{1}{2} \lambda$ out-of-phase, the electric fields between the gaps are constrained to point in opposite directions with respect to adjacent gaps. Thus, the so-called "pi-mode" fields necessary for efficient magnetron-like operation are provided.

The electron cloud rotates about the axis A within the anode-cathode space 44. As the cloud rotates, the electron distribution becomes bunched on its outer surface forming spokes of electronic charge which resemble the teeth on a gear. The operating wavelength (equal to λ) of the phaser 22 is determined by how rapidly the spokes pass from one gap to the next in one half of the oscillation period. The electron rotational velocity is determined primarily by the strength of a permanent magnetic field and the electric field which are applied to the anode-cathode region 44. For very high frequency operation, the phasing lines formed by the waveguides

59a and 59b are spaced very closely to permit a large number of gap passings per second.

The total number N of waveguides 59a and 59b in the anode 42 is selected such that the electrons moving through the anode-cathode space 44 preferably are moving substantially slower than the speed of light c (e.g., approximately on the order of 0.1c to 0.3c). Preferably, the circumference $2\pi r_a$ of the inner surface 50 of the anode is greater than λ , where λ represents the wavelength of the operating frequency. As previously noted, the waveguides 59a and 59b are evenly spaced around the inner circumference of the anode 42, and the total number N is selected so as to be an even number in order to permit pi-mode operation.

In the above discussed embodiment of Figs. 2 and 3, the waveguides 59a and 59b are oriented with their respective E-planes perpendicular to the axis A. The waveguides 59a and 59b are straight tapered waveguides, although it will be appreciated that the waveguides may instead be non-tapered. Moreover, differences in phase length between the respective waveguides may be carried out via other techniques such as providing curved waveguides 59b within the anode 42 versus forming the wider waveguides.

Exemplary dimensions for the anode 42 in an embodiment having non-tapered waveguides 59a and 59b are as follows:

operating frequency: 36.4 Ghz ($\lambda = 8.24 \text{ mm} = 0.324''$)
inner radius r_a : 4.5 mm = 0.177"
outer radius: 24.04 mm = 0.9465"
waveguide 59a: 0.254 mm x 5.32 mm (0.010" x 0.209")
waveguide 59b: 0.254 mm x 7.67 mm (0.010" x 0.302")
number of waveguides along given circumference: 148

As far as manufacture, the cathode 40 of the phaser 22 may be formed of any of a variety of electrically conductive metals as will be appreciated. The cathode 40 may be solid or simply plated with an electrically conductive and emissive material such as nickel, barium oxide or strontium oxide, or may be fabricated from a spiral

wound thoriated tungsten filament, for example. Alternatively, a cold field emission cathode 40 which is constructed from micro structures such as carbon nanotubes may also be used.

The anode 42 is made of an electrically conductive metal and/or of a non-conductive material plated with a conductive layer such as copper, gold, aluminum or silver. The resonant cavity structure 72 may or may not be electrically conductive, with the exception of the walls of the resonant cavity 66 and output port(s) 74 which are either plated or formed with an electrically conductive material such as copper, gold or silver. The anode 42 and resonant cavity structure 72 may be formed separately or as a single integral piece as will be appreciated.

Fig. 4a Figs. 4a and 4b illustrate wedges that may be used to form the anode 42 in one embodiment of the invention. As is explained in the aforementioned U.S. patent application Ser. No. 09/798,623, an anode similar to the anode 42 may be formed by a plurality of pie-shaped wedges. Likewise, the anode 42 may be formed by a combination of wedges 80a and 80b as shown in Figs. 4a and 4b, respectively.

For example, the inner surface 50 of the anode 42 may include a plurality N of waveguide openings spaced circumferentially about a given axial point along the axis A. The number N and dimensions of the openings depends on the desired operating wavelength λ as discussed above. The anode 42 is formed by a plurality N of the pie-shaped wedge elements 80a and 80b, referred to herein generally as wedges 80. When stacked side by side, the wedges 80 form the structure of the anode 42.

Figs. 4a and 4b represent perspective views of the wedge elements 80a and 80b. Each wedge 80 has an angular width ϕ equal to $(2\pi/N)$ radians, and an inner radius of r_a equal to the inner radius r_a of the anode 42. The outer radius r_o of the wedge 80 corresponds to the outer radius r_o of the anode 42 (i.e., the radial distance to the outer surface 68. The front face of each wedge 80a has formed therein the bottom and side surfaces of the even-numbered waveguides 59a. Likewise, the front face of each wedge 80b has formed therein the bottom and side surfaces of the odd-numbered waveguides 59b.

A total of $N/2$ wedges 80a and $N/2$ wedges 80b are assembled together side-by-side in alternating fashion to form a complete anode 42 as represented in Fig. 3. The back face of each wedge 80 thus serves as the top surface of the waveguide formed in the adjacent wedge 80.

5 The wedges 80 may be made from various types of electrically conductive materials such as copper, aluminum, brass, etc., with plating (e.g., gold) if desired. Alternatively, the wedges 80 may be made of some non-conductive material which is plated with an electrically conductive material at least in the regions in which the waveguides 59a and 59b are formed.

10 The wedges 80 may be formed using any of a variety of known manufacturing or fabrication techniques. For example, the wedges 80 may be machined using a precision milling machine. Alternatively, laser cutting and/or milling devices may be used to form the wedges. As another alternative, lithographic techniques may be used to form the desired wedges. The use of such wedges allows precision control of the respective dimensions as desired.

15 After the wedges 80 have been formed, they are arranged in proper order (i.e., even-odd-even-odd..., etc.) to form the anode 42. The wedges 80 may be held in place by a corresponding jig, and the wedges soldered, brazed or otherwise bonded together to form an integral unit.

20 *See a10* Figs. 5 and 6 illustrate another embodiment of the phaser 22 having a different anode structure. More particularly, the phasing lines formed by the waveguides 59a and 59b in the previous embodiment are replaced by interdigital electrodes. The interdigital electrodes permit very fine electrode spacing independent of the operating wavelength λ . As there are many similarities between
25 the respective embodiments described herein, only the relevant differences will be discussed below for sake of brevity.

30 *See a11* As is shown in Figs. 5 and 6, the phaser 22 includes permanent magnets 58 and 60 for providing the cross magnetic field B. Mounted concentrically about the axis A on each of the magnets 58 and 60 is a corresponding cylindrical pole piece 90 made of iron or the like. Each of the pole pieces 90 includes a smooth, highly

Chad A12
electrically conductive cladding 92 made of silver or the like. The pole pieces 90 are generally symmetric and face each other as shown in Figs. 5 and 6. The width W of the pole pieces 90 and corresponding cladding 92 defines a relatively wide anode-cathode space 44 therebetween.

5 In the exemplary embodiment, each pole piece 90 includes a plurality of electrodes 96 equally spaced about the circumference of a circle with a radius r_{cb} from the axis A. The electrodes 96 in the exemplary embodiment are each formed by an electrically conductive pin made of silver, copper, or the like. The electrodes 96 may have a circular or square cross section, for example. The electrodes 96 have a length of $1/4\lambda$, where λ is again the wavelength at the desired operating frequency. The electrodes 96 are mechanically coupled to and extend from the base of the corresponding pole pieces 90 parallel with the axis A. In addition, the electrodes 96 from each pole piece 90 are electrically coupled to the pole piece 90 in this embodiment so as to remain electrically at the same electrical potential as the corresponding pole piece 90. Moreover, the electrodes 96 from the upper pole piece 90 are interdigitated with the electrodes 96 of the lower pole piece 90 as shown in Fig. 5. As a result, a cylindrical "cage" is formed about the cathode 40 in the anode-cathode space 44 defined between the respective pole pieces 90. Adjacent electrodes 96 from the different pole pieces are thus spaced from one another by a gap represented by G_p as shown in Fig. 7. It will be appreciated that the number of electrodes 96 shown in the figures is reduced for ease of illustration.

Chad A12
25 According to the embodiment of Figs. 5-7, the radial distance from the electrodes 96 to the outer edge of the pole pieces 90 (inclusive of the cladding 92) is $\lambda/2$, for example (Fig. 7). The spacing S between the opposing faces 98 of the pole pieces 90 is slightly greater than $\lambda/4$ (to avoid electrode contact with the oppositely facing pole piece 90). As a result, the opposing faces 98 of the pole pieces 90 form a waveguide or parallel plate transmission line having a length along the radial direction of $\lambda/2$ which begins at the edge of the cylindrical cage formed by the electrodes 96 and opens into the common resonant cavity 66.

The cathode 40 extends along the axis A (e.g., through the lower magnet 60 and the pole piece 90) so as to be centered within the cage formed by the interdigital electrodes 96. As in the previous embodiment, terminals 52 and 54 respectively pass through an insulator 55 and are electrically connected to the cathode 40 to supply power to heat the cathode 40 and also to supply a negative (-) high voltage to the cathode 40. The respective pole pieces 90 in this embodiment are electrically connected to the positive (+) or ground terminal of the high voltage supply via terminal 56. During operation, the power supply 32 (Fig. 1) applies heater current to and from the cathode 40 via terminals 52 and 54. Simultaneously, the power supply 32 applies a dc voltage to the cathode 40 and anode 42 via terminals 54 and 56. The dc voltage produces a dc electric field E which extends radially between the cathode 40 and the electrodes 96 throughout the anode-cathode space 44.

Electrons are emitted from the cathode 40 and again follow the aforementioned curved paths through the orthogonal E field and B field in the anode-cathode space 44. The electrons in turn pass in close proximity to the electrodes 96 and induce opposite charges on adjacent electrodes 96 as represented in Fig. 7. The induced charges further induce an electromagnetic signal which radiates outward between the opposing faces 98 of the pole pieces 90 into the resonant cavity 66. The radiated electromagnetic signal is reflected by the resonant cavity 66 back towards the anode-cathode space 44 so as to reinforce the alternating charge which is induced on the adjacent electrodes 96.

In this manner, the energy within the phaser 22 begins to oscillate at the desired operating frequency in conjunction with the electron cloud which forms and rotates within the anode-cathode space 44. Standing-wave electromagnetic fields are established between the straight and curved surfaces of the toroidal resonant cavity 66. A portion of those fields are conducted inward between the opposing faces 98 of the pole pieces 90 toward the interdigital electrodes 96. At a specific instant of time during a cycle of oscillation, the standing-wave fields will cause the face 98 and electrodes 96 of the upper pole piece 90 to be charged negatively while the face 98 and electrodes 96 of the lower pole piece 90 are charged positively.

The resultant alternating positively and negatively charged interdigital electrodes 96 cause horizontal electric fields E_h to exist in the gaps between the electrodes 96 as represented in Fig. 7. As the standing-wave field reverses in time during the cycle of oscillation, the face 98 and electrodes 96 of the upper pole piece 90 become positively charged while the face 98 and electrodes 96 of the lower pole piece 90 become negatively charged. The horizontal electric fields E_h between the electrodes 96 thus reverse in direction during each cycle. These horizontal electric fields E_h thus become the pi-mode fields which interact with the rotating electron cloud within the anode-cathode space to produce oscillations within the phaser 22.

In an embodiment according to Figs. 5-7, exemplary dimensions and characteristics of the phaser 22 are as follows:

desired operating frequency: 10 GHz

diameter of pole pieces 90 (including cladding 92): 3.9 cm

length L_c of resonant cavity 66: 8.86 cm

width W_c of resonant cavity 66: 10.6 cm

electrode 96 (pin) length: $1/4 \lambda$

number of electrodes 96: 40 (20 on upper pole piece; 20 on lower pole piece)

diameter of electrodes 96: 0.020 inch

spacing between electrodes 96 (gap G_p): 0.010 inch.

Figs. 8-10 illustrate another embodiment of the phaser 22. This embodiment is similar to the embodiment of Figs. 5-7, with the exception that the wide anode structure 42 has been replaced with a narrow anode structure 42. Specifically, the diameter of the pole pieces 90 (including the cladding 92) is only slightly larger than the diameter ($2 \times r_{cb}$) of the circle formed by the electrodes 96. Operation is similar to that described above with respect to the embodiment of Figs. 5-7. However, in this embodiment the standing-wave fields in the resonant cavity 66 are applied directly to the interdigital electrodes 96. There is no effective $\lambda/2$ waveguide or parallel plate transmission line between the "cage" formed by the electrodes 96 and the opening to the resonant cavity 66.

The narrow anode embodiment of Figs. 8-10 is particularly useful for constructing a phaser 22 designed to operate at very short wavelengths. This narrow anode design facilitates forming multiple "cages" of interdigital electrodes 96 stacked atop one another along the axis A. Thus, even when the length of the cage
5 pin electrodes 96 become very short at infrared and optical wavelengths, for example, the stacked cages provide a larger interaction surface area within the anode-cathode space 44.

Referring briefly to Fig. 11, an alternate embodiment of the anode 42 is shown in accordance with the present invention. The anode 42 includes a hollow cylindrical
10 tube 110 made of glass or other type of dielectric material. The interdigital electrodes 96 are fabricated as metalized patterns on the inner surface of the tube 110. Thus, simple lithography techniques commonly used with the fabrication of semiconductor devices can be used to form fine, precision interdigital electrodes 96. The tube 110 is then placed along the axis A of the phaser 22 so as to surround the
15 cathode 40 and is located between the magnets 58 and 60 as represented in the other embodiments. The interdigital electrodes 96 each are coupled to ground or a positive dc voltage via respective upper and lower conductive rings 112 and 114 which also are patterned on the surface of the tube 110 along with the interdigital electrodes 96. The tube 110 serves as a support substrate for the electrodes 96
20 formed thereon, particularly at shorter wavelengths when the electrodes 96 become quite small.

In addition, the tube 110 can serve as an outer vacuum envelope. Outside the tube 110, the phaser 22 (e.g., resonant cavity 66) may be filled with air. Meanwhile, the interdigital electrodes 96 formed on the inner surface of the tube 110
25 are exposed to the vacuum and the rotating electrons emitted from the cathode 40. Air cooling against the outer wall of the tube 110 can be used to cool the interdigital electrodes 96 on the inner surface.

Thus, the tube 110 is convenient as it surrounds the cathode 40 and can be the only portion of the device 22 which contains a vacuum. The portions of the tube
30 110 which do not include the interdigital electrodes 96 may include a metalized film

on the inner surface so as to be electromagnetically reflective as desired. The tube 110 with electrodes 96 and the anode 40 may be formed as a composite structure in much the same manner as linear light bulbs with electrical connections at the ends and a vacuum inside.

5 Fig. 12 illustrates yet another embodiment of the phaser 22 in accordance with the present invention. The embodiment is similar to the embodiment of Figs. 5-7 with the following exceptions. In this embodiment, the interdigital electrodes 96 are held at a positive high dc voltage and are isolated from the pole pieces 90. As is shown in Fig. 12, the interdigital electrodes 96 associated with each pole piece 90 are respectively formed on and extend from an electrically conductive ring 120. Each ring 120 is electrically isolated from its corresponding pole piece 90 by an insulating spacer 122.

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9765
9770
9775
9780
9785
9790
9795
9800
9805
9810
9815
9820
9825
9830
9835
9840
9845
9850
9855
9860
9865
9870
9875
9880
9885
9890
9895
9900
9905
9910
9915
9920
9925
9930
9935
9940
9945
9950
9955
9960
9965
9970
9975
9980
9985
9990
9995
10000
10005
10010
10015
10020
10025
10030
10035
10040
10045
10050
10055
10060
10065
10070
10075
10080
10085
10090
10095
10100
10105
10110
10115
10120
10125
10130
10135
10140
10145
10150
10155
10160
10165
10170
10175
10180
10185
10190
10195
10200
10205
10210
10215
10220

pieces and/or conductive rings. Such connections provide increased DC continuity if desired.

It will be appreciated that the phaser 22 is described herein in the context of an anode structure which surrounds the cathode. In an alternate embodiment, the structure may be inverted. The anode may be surrounded by a cylindrical cathode. The present invention includes both inverted and non-inverted forms.

Although the invention has been shown and described with respect to certain preferred embodiments, it is obvious that equivalents and modifications will occur to others skilled in the art upon the reading and understanding of the specification.

The present invention includes all such equivalents and modifications, and is limited only by the scope of the following claims.